



CAF

Convertidor eléctrico magnético
Magnetic electric converter

CAF Advanced

Potencia y tecnología

Convertidor eléctrico monofásico o trifásico

Power and technology

Single-Phase or Three-Phase electric converter

Cable / Cable: 5 m



Pulsador Marcha-Paro y mayor protección
Start&stop push button and higher protection

Resistencia: bastidor de acero de protección
Movilidad: cuerpo de aluminio ligero y bastidor de transporte
Seguridad: pulsador marcha-paro con relé térmico y protección de fallo de fase o descompensación
Potencia: motor eléctrico de alto rendimiento
Multifuncional: algunos modelos permiten conexiones simultáneas de agujas
Calidad: materiales resistentes a la abrasión

Resistance: protection steel frame
Mobility: lightweight aluminum body and transport frame
Security: start & stop button with thermal relay and protection against phase failure or descompensation
Power: high performance electric engine
Multifunctional: some models allow simultaneous poker connections
Quality: abrasion resistant materials

Agujas para convertidor eléctrico CAF / Pokers for CAF electric converter

AV

Aguja eléctrica 42V
42V electric poker
P. 18



ERGO

Aguja eléctrica con empuñadura 42V
42V electric poker with handle
P. 22



Entrada / Input	230V 50Hz 1Ph
Salida / Output	42V 200Hz 3Ph
Protección / Protection	IP44

Datos técnicos Technical data		CAF Monofásicos / Single-Phase		
		100M	120M	140M
Entrada Input	A	6,5	6,6	8,5
Salida Output	kVA	1	1,2	1,5
	A	14	18	21
Bases Outlets	<i>i</i> Nr.	1	2	2
Peso Weight	Kg	25	25	36
		10.066	10.086	*10.069

Entrada / Input	400V 50Hz 3Ph
Salida / Output	42V 200Hz 3Ph
Protección / Protection	IP44

Datos técnicos Technical data		CAF Trifásicos / Three-Phase				
		110T	130T	150T	220T	600T
Entrada Input	A	2,6	2,6	3,5	6	11
Salida Output	kVA	1	1,2	1,5	2,2	2x2,2
	A	14	18	21	30	2x30
Bases Outlets	<i>i</i> Nr.	1	2	2	3	4
Peso Weight	Kg	24	24	32	43	95
		10.065	10.087	*10.040	*10.043	*10.095

i **Posibilidades de conexión de agujas:** la suma de intensidades de las agujas (A) a conectar no ha de superar la intensidad de salida del generador (A)
Pokers connection possibilities: pokers intensity sum (A) to connect must not exceed generator output intensity (A)



CAF220T

Indicar al final de la referencia .CR para solicitar con ruedas y asa de transporte
 Note at the end of the reference .CR to order with wheels and carrying handle



CAF600T

Incluye de serie ruedas y asa de transporte
 Includes wheels and carrying handle as standard features