

T-ERGO PLUS

ELECTRONIC POKER WITH CONVERTER BUILT-IN

VERSATILE AND EFFICIENT IDEAL FOR VERTICAL WORK



**** LED SCREEN
Technology for viewing:**

Shorts circuit	Overloads
Ground leaks	Overvoltage
Phase loss	Overheating

Description:




Poker and electronic converter integrated in just one device. Operates with single-phase connection **230V/50-60Hz or 110-130V/ 50-60Hz.**

Ideal for vertical work, incorporates an ergonomic handle. For use in continuous or heavy work and large-scale constructions.


Main Features:

- **RESISTANCE** Aluminum box, hermetic and shockproof.
- **MOBILITY AND COMFORT** Easy to handle and transport, converter and poker in a single equipment.
- **SECURITY** Protection device against tension fluctuations, current leakage, overload, phase losses, short circuit and overheating.
- **DESIGN** Ergonomic with rounded edges that prevent snagging. Comfortable grip for vertical works.
- **QUALITY** Abrasion resistant materials.
- **EASY REPAIR** EASY REPAIR Incorporates a quick system to remove and replace the electronic components.
- **HIGH PERFORMANCE** at stable speed.
- **ENERGY EFFICIENCY**


Quick View:

- 1 On/off easily accessible button.
- 2 Led screen technology for viewing errors. *
- 3 Aluminum housing with electronic device built in. 2CV (Ø 38, 42, 52, 58).
- 4 Plug - 2Ph+E
- 5 Supply cord according to CE regulations and special for outdoors, 5¹ 5m y 5² 10m. 
- 6 Steel cap. 
* Optionally available in rubber cap.
Anti-abrasive rubber that does not damage wooden formwork.
- 7 Steel poker head.
- 8 Rubber hose – 0,7 m. 
- 9 Ergonomic housing with on/off button and easy-to-hold grip.

Specifications and References:

Connection:	Single-phase	Input:	230V / 50-60Hz / 1 Ph
Speed:	12.000 v.p.m		110-130V / 50-60Hz / 1 Ph
Protection:	IP 44-57	Output:	230V / 200Hz / 3 Ph
Rubber hose:	0,7 m 		110V / 200Hz / 3 Ph



Ref. 230 V	Ref. 110 V	MODEL	Thermal	Ø mm	Power Kw/Hp	Intensity 		Vibration m³/h	Weight Kg
						A - 230V	A - 110V		
10450	10458	T-ERGO PLUS 38T	✓	38	1,5/2	1,3	3,7	20	10
10451	10459	T-ERGO PLUS 42T	✓	42	1,5/2	1,8	4,5	25	11
10452	10460	T-ERGO PLUS 52T	✓	52	1,5/2	2,6	5,1	40	12
10453	10461	T-ERGO PLUS 58T	✓	58	1,5/2	3,0	6,1	45	14

 Estimated consumption (A) of unloaded pokers

 Special lengths upon request